

MultiCom 500 GSM Apartment Intercom



Up to...
500 Flats!

Key Features.

- Multi apartment or resident wireless system
- Up to 500 apartments
- Can register 3 phones per flat
- Directory system
- 2 Relays – Controlled via phone
- Customised welcome screen
- Stainless Steel with Blue LED light
- Keypad access available
- Rain hood

*With a customised welcome message, the MultiCom system is activated when a visitor taps in the apartment number into the keypad. This then calls a mobile or landline number to the flat or apartment, allowing the tenant to open and close the door using the * and # button from their telephone device. If the tenant is unavailable, the MultiCom system bounces to another phone, then another allowing 3 tenants to answer the call. With 3 phones for 500 apartments, the MultiCom system can hold 1500 different call combinations in the stylish stainless steel system. Programmable by SMS Text, PC USB Link or on-screen keypad, the system also has a directory system, in case the visitor is unsure of the flat or apartment number via sim card. This is activated with a scroll option.*

Digital Directory
up to...1500
numbers!



Power Supply	12-15vdc(adaptor inc)	GMS Modem	Quad band 850/900/1800/1900
Current Consumption	100mA standby, 350A dialling	Modem approvals	CE & FCC
Relay Outputs	1	Programming method	SMS & keypad on screen
Relay Type	N/O & N/C contacts	Caller ID	No
Relay Time	Adjustable 1.9999 Sec	Relay Control	By phone



127mm	Width
290mm	Height
90mm	Max Thick

194mm	Vertical fixing centres
80mm	Horizontal fixing centres
20mm	Cable entry
70mm	Cable entry to bottom
43mm	Screw fixing to bottom